

150 Dodd Street SE Marietta, GA. 30060

Phone: 770-973-6251 Fax: 678-401-3854 Email: <u>info@mgs4u.com</u> Website: <u>www.mgs4u.com</u>

RP-TNC male to BNC female Adapter



#### **Technical Data Sheet**

This RP-TNC to BNC female male adapter is one of several thousand RF products available from Max-Gain Systems, Inc. This adapter is a between series coaxial adapter.

This adapter is made from a Solid Brass body that is precision machined and plated with Nickel for superior performance and value. This RP-TNC male to BNC female adapter has a Delrin dielectric and a gold plated brass center pin. The BNC female side provides tabs or "bayonets" for quick and reliable connections and disconnections. The RP-TNC male side provides the jack that is normally found in a TNC female connection and internal threads, RP-TNC connections are popular in wireless and Wi-Fi applications.

#### **Material Specifications**

RP-TNC male to BNC female Adapter		Part Number 8601
Description	Material	Plating
Insulator	Delrin	White
Shell	Brass	Nickel
Pin	Brass	Gold
Insulator	Delrin	White
Body	Brass	Nickel

## **Mechanical Specifications**

Size	Dimension
Length	1.10 in (28 mm)
Width	0.57 in (14.5 mm)
Height	0.57 in (14.5 mm)
Weight	0.5 oz (14 g)

# **Environmental Specifications**

Temperature	Spec
Operating Range	-65 to +165 deg C

# Compliance Certifications (see product page for current documentation)

**Availability** Click the following link (or enter part number in the "SEARCH" bar at the top of any page of the website) to obtain additional part information including price, inventory and certifications: <u>https://mgs4u.com/product/rp-tnc-male-to-bnc-female-adapter-8601/</u>

