



150 Dodd Street SE  
Marietta, GA. 30060

**Phone:** 770-973-6251  
**Fax:** 678-401-3854

**Email:** [info@mgs4u.com](mailto:info@mgs4u.com)  
**Website:** [www.mgs4u.com](http://www.mgs4u.com)

BNC male to BNC female Right Angle Adapter



## Technical Data Sheet

This BNC male to BNC female right angle adapter is one of several thousand RF products available from Max-Gain Systems, Inc. This adapter is an in-series coaxial adapter.

This adapter is made from a Solid Brass body that is precision machined and plated with Nickel for superior performance and value. This BNC male to BNC female adapter has a Delrin dielectric and a gold plated brass center pin. The BNC male side accepts the BNC female tabs or “bayonets” for quick and reliable connections and disconnections. The BNC female side’s tabs or “bayonets” accepts the BNC male for quick and reliable connections and disconnections.

## Material Specifications

### BNC male to BNC female Adapter

**Part Number 7048-RA**

Description	Material	Plating
Shell	Brass	Nickel
Center Pin	Brass	Gold
Insulator	PTFE	White
Body	Brass	Nickel

## Mechanical Specifications

Size	Dimension
Length	1.07 in (27.4 mm)
Width	0.93 in (23.6 mm)
Height	0.57 in (14.50 mm)
Weight	0.42 oz (12 g)

## Environmental Specifications

Temperature	Spec
Operating Range	-65 to +165 deg C

## Compliance Certifications (see product page for current documentation)

**Availability** Click the following link (or enter part number in the “SEARCH” bar at the top of any page of the website) to obtain additional part information including price, inventory and certifications: <https://mgs4u.com/product/bnc-male-to-bnc-female-right-angle-adapter-7048-ra/>

