



150 Dodd Street SE  
Marietta, GA. 30060

**Phone:** 770-973-6251  
**Fax:** 678-401-3854

**Email:** [info@mgs4u.com](mailto:info@mgs4u.com)  
**Website:** [www.mgs4u.com](http://www.mgs4u.com)

BNC female to Type N male Adapter



## Technical Data Sheet

This BNC female to Type N male adapter is one of several thousand RF products available from Max-Gain Systems, Inc. This adapter is a between series coaxial adapter.

This adapter is made from a Solid Brass body that is precision machined and plated with Nickel for superior performance and value. The BNC female provides tabs or “bayonets” for quick and reliable connections and disconnections. This Type N male to BNC female adapter has a delrin dielectric and a gold plated brass center pin. The Type N male side contains a gasket, for shock / vibration resistant and waterproof connections.

## Material Specifications

### BNC female to Type N male Adapter

Part Number 7324

Description	Material	Plating
Shell	Brass	Nickel
C Ring	Brass	None
Gasket	Silicone	Orange
Pin	Brass	Gold
Insulator	Delrin	White
Body	Brass	Nickel

## Mechanical Specifications

Size	Dimension
Length	1.27 in (32.3 mm)
Width	0.78 in (20 mm)
Height	0.78 in (20 mm)
Weight	1.2 oz (36 g)

## Environmental Specifications

Temperature	Spec
Operating Range	-65 to +165 deg C

## Compliance Certifications (see product page for current documentation)

**Availability** Click the following link (or enter part number in the “SEARCH” bar at the top of any page of the website) to obtain additional part information including price, inventory and certifications: <https://mgs4u.com/product/bnc-female-to-type-n-male-adapter-7324/>



**MGS** MAX-GAIN  
SYSTEMS, INC.

**TITLE: BNC female to Type N male Adapter**

CAGE CODE: 7JZZ8