

Fixed Vacuum Capacitors

P/N#	Jennings P/N# (cross ref.)	Comet P/N# (cross ref.)	Capacitance Pf	Voltage KV Peak testing	Voltage KV Peak Working	Current Max. RMS A	Length mm/inch	Diameter mm/inch
CKT-6-0035	CKT-6-0035	---	6 +/-5%	35.0	25	47	165.1/6.5	58.9/2.32
CKT-12-0035	CKT-12-0035	CF3C-12G	12 +/-5%	35.0	25	52	165.1/6.5	58.9/2.32
CKT-25-0035	CKT-25-0035	CF3C-25H	25 +/-5%	35.0	25	67	165.1/6.5	58.9/2.32
CKT-50-0035	CKT-50-0035	CF3C-50G	50 +/-5%	35.0	25	77	165.1/6.5	58.9/2.32
CKT-75-0035	CKT-75-0035	CF3C-75E	75 +/-5%	35.0	25	82	165.1/6.5	58.9/2.32
CKT-100-0035	CKT-100-0035	CF2C-100F	100 +/-5%	35.0	25	87	165.1/6.5	58.9/2.32



CKT6, 12, 25, 50, 75 and 100
CONTINUOUS RMS AMPERES vs. FREQUENCY
(at 25kV PEAK WORKING VOLTAGE)

